09

HIGH FREQUENCY ONLINE UPS



High Frequency Online Single Input Single Output Three Input Single Output UPS 6KVA to 30KVA



FUNCTIONS

- Real-time Dual Conversion
- Microprocessor control ensures high reliability
- Power factor up to 0.9
- Wide input voltage range(110V-300V)
- Output sine wave, compatible with generators
- Optional SNMP card for independent or seamless monitoring with RS232

APPLICATIONS FIELDS

Widely used in network management centers and computers, banks, securities, taxation, communications, postal services, radio and television, public security, transportation, electric power, medical, industrial control, national defense and other important data fields.

Model		SP6K(S)	SP10K(S)	3C10K(S)	3C15K(S)	3C20K(S)	3C30K(S)
Phase		Single-input single-output		Three-input single-output			
Capacity		6KVA 5400W	10KVA 9000W	10KVA 8000W	15KVA 12000W	20KVA 16000W	30KVA 24000W
Input							
Input Voltage		208/220/230/240VAC 380/400VAC/415VAC (3ph + N)					
Voltage range		110-300VAC @ 50% load 190-520VAC (3-phase + N) @ 50% load 176-300VAC @ 100% load 305-520VAC (3-phase) @ 100% load					
Input Frequency		46~54Hz or 56~64Hz					
Power Factor		≥0.99@100% load ≥0.8@100% load					
Output							
Output Voltage		208/220/230/240VCA					
AC voltage regulation		±1%					
Frequency (Synchronous correction range)		46-54Hz/56-64Hz					
Frequency Range (Battery Mode)		50Hz/60I	Hz±0.1Hz	50Hz/60Hz±0.2Hz			
Surge Rating		3:1(max) 3:1(max)					
Waveform balance		≤3% THD (Linear Load) ≤5% THD (Non-linear Load)					
Transfer Time		0ms					
Output Waveform		Pure Sine Wave					
			Efficienci				
Mains Mode		93%	94%	91%	91%	93%	91%
Battery Mode		90%	91%	91%	91%	92%	90%
Battery	I=						
Stardard UPS	Battery Model		1	12V/7AH			
	Battery quantity	16	16	16/20	16/20	16/20	
	Charging time	9 hours to 90% full capacity					
	Wax Griarging Gurrent	Preset1A , 1A/2A 4A adjustable					
	Charging voltage	218.4VDC±1%/273VDC±1%					
External battery UPS	Battery Model	Depends on the applicant					
	Battery quantity	16-20 adjustable					
	Max charging current	1A/2A/4A/6A adjustable Preset 4A, 1A/2A/4A adjustable					
	Charging voltage		218.4VDC±1%, 273VDC±1%				
Display In	nstructions						
LCD		Load size, battery capacity, mains mode, battery mode, bypass mode, fault indication					
Physical	performance						
Stardard UPS	Size (MM)	500*24	48*616	500*248*620			
	Weight (KG)	57	68				
External battery UPS	Size (MM)	500*248*460		575*248*620		815*250*826	
	Weight (KG)	18	20	27	35	35	64
Usage en	vironment						
Humidity		20-95%RH@0-45℃ (No condensation)					
Noise		<60dbA@1M					
Control Management							
Smart RS-232/USB		Be in favor of Supports Windows® 2000/2003/XP/Vista/2008, Windows® 7/8, Linux, and MAC					
Optional SNMP		Power management supports SNMP management and network management					

Products specifications are subject to change without further notice